

Electronic Control Panel

Your steam shower is fitted with an electronic control panel that allows you to operate the electronic features of your shower. From the control panel you can control the lights, Steam, Radio, and Bluetooth audio.



Power ON / OFF

In standby mode this button is lit Red. Press and keep pressing the power button until the panel beeps and the light turns Blue. The Panel is now active.



If the panel is not used for 30 seconds, the panel will LOCK. This is noted by the lines in the display FLASHING.

To deactivate the LOCK, simply press and hold the button until a beep is heard and the lines stop flashing.



LIGHTS

This model comes with an LED light surrounding the monsoon. Press the light button. With each press, the display will show ON1, ON2, ON3, OFF. The panel is able to accept up to three different light relays, hence the various light modes. Toggle to OFF to turn the light off.



STEAM

Pressing the Steam button activates the steam Generator.

Press the M button to toggle between the Temperature and Duration/Time settings. Temperature is the setting the cabin will try to maintain inside the cabin and duration is the length of time you plan to use the steam. Do NOT use the steam function for longer than 15 minutes in a session, allowing to fully cool before re-use.



FAN

The circulation fan can be activated to draw air/steam inside the cabin out. This may be used in conjunction with the steam.



OZONE

Close the shower doors and press the Ozone button. Leave the shower to carry-out this process which takes approximately 10 minutes. then open the doors and allow the shower to fully air dry. This device does not may any audible or visual notification other then the panel display, but the aroma of Ozone may be noticeable when you open the doors. The Power button flashes during this process.



ARROWS

The Arrow buttons control Tuning, Volume, Track Skip etc depending upon which mode is currently selected.



REMOVE PROTECTIVE FILM ON CONTROL PANEL BEFORE USE

M The button can be used to Store Radio stations into Memory. The button also serves as a toggle the function of the ARROW keys for time/temperature/track/volume/tuning etc.

TUN

Pressing this button will allow you to enter the tuning mode when the Radio is activated. The current frequency will be displayed and by using the Arrow keys can adjust the precise frequency.



BLUETOOTH

Pressing this button will allow you to receive audio played from Bluetooth enabled device. You can control volume and skip tracks as described for the USB option. You will have to PAIR the shower to a Bluetooth device first - see following page. When this mode is activated then Power button will be lit Red.



RADIO

This button activates the built in FM Radio. In this mode the power button will be lit White. Pressing the TUN button and then using the ARROW buttons allows you to change radio frequency.